

Armoured Instrumentation 300V 16awg SPOS



16 awg Stranded tinned soft copper, ASTM B8, B33, 300v XLPE insulation, **twisted into pairs**, individually Shielded Pairs with a stranded tinned copper drain wire, polypropylene fillers, polyester separator tape, overall aluminum/mylar shield with tin copper Drian wire, FR LAG PVC Inner jacket, aluminum interlocked armour, grey FT4, FR, LAG PVC outer jacket

Specifications and Compliance: CSA C22.2 No. 239, Control and instrumentation cables, CSA C22.2 No. 174, cables and cable glands for use in hazardous locations, • CSA C22.2 No. 38, Thermoset-insulated wires and cables; • CSA C22.2 No. 75, Thermoplastic-insulated wires and cables; • CSA C22.2 No. 2556/UL 2556 FT4, Vertical Tray

Flame Test rate: CSA FT4, IEEE 383/1202 (70,000 BTU/hr.), Vertical Flame Test rated

16 awg Stranded Tinned Copper Pairs SPOS (Shielded pairs & Overall Shield) 300v

RW Part No.	Number Of Pairs	Insulation Thickness in	Inner Jacket O.D. in	Armour O.D. in	Cable O.D. in	Cable Weight kg/km	Max Pulling Tension lbs	Min Bend Radius in
IA16-01-PA4	1	0.025	0.316	0.516	0.620	238	41	7.4
IA16-02-PA4	2	0.025	0.567	0.767	0.874	463	248	10.5
IA16-04-PA4	4	0.025	0.605	0.805	0.912	529	165	10.9
IA16-06-PA4	6	0.025	0.721	0.921	1.029	674	248	12.3
IA16-08-PA4	8	0.025	0.782	1.017	1.126	849	330	13.5
IA16-12-PA4	12	0.025	.989	1.224	1.335	1187	495	16

All dimensions are nominal and are subject to normal manufacturing tolerance. Specifications are subject to change without notice.

Armoured Instrumentation 300V 16awg SPOS

Colour Coding

- Multi Pairs – Black, & white, number-coded with black ink printed on white conductor

Features

- HL rated for use in hazardous locations
- UV sunlight resistant
- “SUN RES” (all colours)
- Meets cold bend and impact tests at (-40°C)
- Direct burial rated

Application

- For wet and dry locations
- To be used for exposed and concealed wiring or where subjected to the weather.
- For use in ventilated, non-ventilated and ladder-type cable
- Direct burial
- HL rated for use in
- For use in all hazardous locations with proper connectors